Ultrasonic Sensor





Applications

Applications include Burglar Alarms, Distance Measurement, Range Finders, Remote Controllers & Robotics, etc.

Features

- High reliability
- · Compact and light weight
- · Open structure and dual use (Transmitter & Receiver)
- · High sensitivity and sound pressure
- · Less power consumption

Technical Terms

Construction : Open Structure

Using Method : Dual Use (Transmitter & Receiver)


Frequency : 40 ±1kHz


Sound Pressure Level : min. 110dB (10V/30cm)
Sensitivity : min.-65dB/V/µbar
Capacitance : 2500pF ±25% @ 1kHz


Directivity : 50°

Operating Temperature Range : -40°C to +85°C
Storage Temperature Range : -40°C to +85°C
Detectable Range : 0.7 to 18m
Maximum Input Voltage : 60Vp-p
Housing Material : Aluminium

Diagram







Tolerance: ±0.5

Dimensions : Millimetres


www.element14.com www.farnell.com www.newark.com





Ultrasonic Sensor



Beam Pattern:








Directivity in Overall Sensitivity

Test Circuit:



OSC. :Oscillator

F.C :Frequency Counter U.S :Ultrasonic Sensor

S.C.M:Standard Cappacitor Microphone

Amp. : Ampifier

Part Number Table

Description	Part Number
Ultrasonic Sensor, Transceiver, 16mm Dia, 40kHz, -65dB, Aluminium, Silver, -40°C to 85°C	MCUSD16A40S12RO

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

